

### **Microsemi Corporation**

January 19, 2016

## **Product Discontinuance Notification (PDN)**

## Subject: Notice of Last Time Order and Manufacture Discontinuance of XL-GPS Time and Frequency Receiver

Microsemi® offers a last time order opportunity prior to the discontinuance of the items listed below. Last time buy orders must be received by the Last Time Order date.

Part Number	Model Description	Alternative Model*	Alternative Part Number(s)*	Last Time Order	MD	Last Ship Date	EOL
1530-602-1	XL-GPS Time & Frequency Receiver	SyncServer S650 or the XLi Time & Frequency System	Contact Microsemi	Sep 30, 2016	Oct 1, 2016	Nov 30, 2016	Sep 30, 2018
87-399-30	осхо	SyncServer S650 or the XLi Time & Frequency System	Contact Microsemi	Sep 30, 2016	Oct 1, 2016	Nov 30, 2016	Sep 30, 2018
87-8134-1	Expansion Module	SyncServer S650 or the XLi Time & Frequency System	Contact Microsemi	Sep 30, 2016	Oct 1, 2016	Nov 30, 2016	Sep 30, 2018
87-8108 1, 5, 10 MHz Sinewave		SyncServer S650 or the XLi Time & Frequency System	Contact Microsemi	Sep 30, 2016	Oct 1, 2016	Nov 30, 2016	Sep 30, 2018
87-8108	1, 5, 10 MPPS Output	SyncServer S650 or the XLi Time & Frequency System	Contact Microsemi	Sep 30, 2016	Oct 1, 2016	Nov 30, 2016	Sep 30, 2018

\***Note:** The functionality found in the XL-GPS is available in either the SyncServer S650 with one or more Timing I/O modules and possibly the FlexPort option enabled, or the more modular XLi Time and Frequency System. Contact Microsemi Sales for the best alternative for your requirements.

## Definitions

**Manufacture Discontinuance (MD)**: MD means product will no longer be manufactured or available for sale beginning with the date specified above.

Microsemi Corporation One Enterprise, Aliso Viejo CA 92656 USA Within the USA: +1 (949) 380-6100 · Sales: +1 (949) 380-6136 Fax: +1 (949) 215-4996 · www.microsemi.com



Last Time Order Date: Orders for this product must be received by this date.

**End of Life:** EOL means product will no longer be repaired or serviced except if under an extended coverage service contract.

### **Support Policy**

Repair services will be available on a repair or replacement basis during the warranty/contract period. In the event of parts or component obsolescence, repairs will be made on a best efforts basis until the end of life. All other service options (telephone technical support, training, etc.) are available from Microsemi Frequency and Time Division's service and support organization on a contract or case-by-case basis. Interested customers should contact the Microsemi Frequency and Time Division to check a product's eligibility for services and any applicable terms.

If you have any questions regarding this letter or would like to inquire about other product support services (e.g. Installation, Telephone Technical Support, Maintenance, Training, etc.) please contact our Customer Assistance Center at 1-888-367-7966 (Toll Free) or 1-408-428-7907, your Sales Representative, or our website **www.microsemi.com** 

Microsemi Frequency and Time Division is highly committed to the Frequency & Time technology market and the customers we serve. We thank you for your understanding and look forward to serving you in future.

Microsemi Corporation

Any projected dates in this notification are based on the most current product information at the time this PDN is being issued, but they may change due to unforeseen circumstances. For the latest schedule and any other information, please contact your local Microsemi Sales Office, the factory contact shown above, or your local distributor.

This PDN is confidential and proprietary information of Microsemi and is intended only for distribution by Microsemi to its customers, for customers' use only. It must not be copied or provided to any third party without Microsemi's prior written consent.

Microsemi Corporation One Enterprise, Aliso Viejo CA 92656 USA Within the USA: +1 (949) 380-6100 · Sales: +1 (949) 380-6136 Fax: +1 (949) 215-4996 · www.microsemi.com

DATASHEET



# SyncServer S650

Accurate, Secure, and Flexible Time and Frequency Standard



0

## **Key Features**

- <15 ns RMS to UTC (USNO)
- <1x10<sup>-12</sup> Frequency accuracy
- Modular timing architecture with unique and innovative FlexPort™ technology
- Most popular timing signal inputs/ outputs are standard in the base Timing I/O module (IRIG B, 10 MHz, 1 PPS, etc.)
- Four GbE ports standard, all with patented NTP hardware timestamping
- Web-based management with highsecurity cipher suite
- -20°C to +65°C operating temperature, shock & vibration qualified
- IPv6/IPv4 on all ports
- Rubidium Atomic Clock or OCXO oscillator upgrades
- Dual power supply option
- PTP and GLONASS ready, no additional hardware required

## **Key Benefits**

- FlexPort<sup>™</sup> timing technology efficiently and cost-effectively adds innovative "any signal, any connector" technology, eliminating the wasted space inherent with legacy style fixed-signal modules/ BNCs
- Multiple GbE network ports for easy network configuration and adaptation
- Reliable and rugged design for long product life and wide application scope
- Many security-hardened, networkbased features for stringent IA requirements.

## **Unparalleled Flexibility**

The modular Microsemi SyncServer S650 combines the best of time and frequency instrumentation with unique flexibility and powerful network/security-based features.

The base Timing I/O module with 8 BNC connectors comes standard with the most popular Timing I/O signals (IRIG B, 10 MHz, 1 PPS, and so on). When more flexibility is required, the unique Microsemi FlexPort™ Technology option enables 6 of the BNCs to output any supported signal (time codes, sine waves, programmable rates, and so on), all configurable in real time via the secure web interface. This incredibly flexible BNC-by-BNC configuration makes very efficient and cost-effective use of the 1U space available. Similar functionality is applied to the 2 input BNCs as well. Unlike legacy modules with fixed count BNCs outputting fixed signal types per module, with FlexPort™ technology you can have up to 12 BNCs output in any combination of supported signal types.

This level of timing signal flexibility is unprecedented, and can even eliminate the need for additional signal distribution chassis as there is no degradation in the precise quality of the coherent output signals.

## **Robust Timing and Design**

The 72-channel GNSS receiver coupled with Microsemi's patented Active Thermal Technology Compensation provides excellent accuracy of <15 ns RMS to (USNO). Backstop this with a UTC durable hardware design subjected to MIL-STD-810G high-reliability testing, components extending the operating temperature range to a very wide -20°C to +65°C, and a dual power supply option. Further, upgrading to a high performance oscillator, such as a Rubidium atomic clock, keeps the S650 accurate for long periods in the event of a GNSS service disruption.

## Secure Networking

Security is an inherent part of the SyncServer S650. In addition to many security features and protocols, unsecure access protocols are deliberately omitted while remaining services can be disabled.

The four standard GbE ports accommodate more than 10,000 NTP requests per second using hardware time stamping and compensation. All network traffic to the S650 CPU is bandwidth-limited for protection against denial-of-service (DoS) attacks. For more secure NTP operations, enable the optional Security-Hardened NTP Reflector<sup>™</sup> with line speed, 100% hardware-based NTP packet processing\*. The Reflector is also a CPU-protecting firewall, bandwidth limiting non-NTP traffic to the CPU. It is also equipped with DoS detection, notification, and protection against abnormally high network traffic.

#### Leverage Built-In Hardware

The SyncServer S650 includes additional built-in hardware features that are enabled through software license keys, such as the Security-Hardened NTP Reflector™. Anticipated future software enabled hardware options are GbE PTP operations and GLONASS support.

The SyncServer S650, the future of time and frequency, today.

\* NTP Reflector is part of the Security Protocol License and will appear in version 1.1 due April 2016.

### Four GbE Ports for Performance, Flexibility, and Security

The S650 has four dedicated and isolated GbE Ethernet ports, each equipped with NTP hardware time stamping. These are connected to a very high-speed microprocessor with microsecond accurate time stamps to assure high-bandwidth NTP performance. This more than meets the need of servicing 10,000 NTP requests per second.




Four GbE ports provide network configuration flexibility and enhanced security. "Multiple" isolated and synchronized time servers can also be configured.

Multiple ports provide the flexibility to adapt to different network topologies as networks grow and change. An S650 can be the single time-source to synchronize clients on different subnets and physical networks. Since each port is independent, it can appear as though there are four clocks available, even though there is only a single time reference.

NTP can be served on all 4 ports. The highly secure web-based management interface is only available on port 1 so that administrators may choose to keep that IP address private and secure. Unique access control lists per port can govern server response to client requests for time.

# Intuitive, Secure and Easy to Use Web Interface

The modern web interface is the primary control interface of the S650. Once the keypad and display are used to bring the unit online, complete status and control functions are easily found via the well organized left side-expanding/collapsing navigation menu.



At a glance dashboard presentation combined with logical organization and intuitive controls make configuring the S650 quite easy.

#### Standard Management Access Security

All of the expected network management protocols are standard in the S650. These include mandatory password access, HTTPS/SSL only (using the high encryption cipher suite), SSH, access control lists, service termination, SNMPv2/v3, and NTP MD5 authentication. All traffic to the S650 CPU is bandwidth-limited for protection against DoS attacks. The local keypad on the server can be password-protected to prevent tampering.

# Security-Hardening Option

The SyncServer S650 can be seriously hardened from both an NTP perspective and an authentication perspective through the Security Protocol License Option, which includes the Security-Hardened NTP Reflector.

**Operational Hardening**—via the 120,000 NTP packet per second NTP Reflector<sup>™</sup> with 100% hardware based NTP packet processing also works with a CPU-protecting firewall by bandwidth limiting all non-NTP traffic. The Reflector also monitors packet flow for DoS detection and reporting, yet remains impervious to the level of network traffic as it operates at line speed.

Authentication Hardening—is available for NTP client/server authentication through the NTP Autokey function or user access authentication via TACACS+, RADIUS and LDAP. (See the *SyncServer Options datasheet* for more detail on the Security Protocol License Option).

Security ~
Users
Access Control
Services/Sys. Control
- HTTPS
- SSH
NTPd Symmetric Keys
NTPd Autokey Server
NTPd Autokey Client
RADIUS
TACACS+
LDAP

An entire drop down menu in the S650 is dedicated to security related protocols.

## Unprecedented NTP Accuracy

The Stratum 1 level S650 derives nanosecond accurate time directly from the atomic clocks aboard the GNSS satellites. By using an integrated, 72-channel GNSS receiver, every visible satellite can be tracked and used to maintain accurate and reliable time. Even in urban canyon environments where direct satellite visibility can be limited, manually inputting the position can be sufficient to acquire accurate time from as few as one intermittent satellite.

# Ultra High Performance NTP

S650 The can effortlessly support hundreds of thousands of network clients while maintaining microsecond caliber NTP timestamp accuracy. NTP request throughput rates exceed 10,000 requests/ second while maintaining NTP timestamp accuracy. If the Security License option is enabled, the NTP Reflector™ can process over 120,000 NTP requests per second with 15 nanosecond caliber time stamp accuracy with the added benefit of security hardening the network port. This can easily translate into sub-millisecond typical NTP client synchronization accuracy on a LAN.

## More Timing I/O Standard

The Base S650 can host two modules. The Timing I/O module is equipped with 8 BNC connectors for timing signal input and output. The standard configuration offers a broad yet fixed selection of signal I/O including IRIG B, 10 MHz, 1 PPS, and so on.



# FlexPort<sup>™</sup>, the Ultimate in Timing Flexibility

Microsemi's unique FlexPort<sup>™</sup> Technology efficiently and cost-effectively adds innovative "any signal, any connector" technology, eliminating the wasted space inherent with legacy style fixed signal modules/BNCs.

The FlexPort<sup>™</sup> Technology option enables the 6 output BNCs (J3-J8) to output any supported signal (time codes, sine waves, programmable rates, and so on.) all configurable in real time through the secure web interface. The 2 input BNCs (J1-J2) can support a wide variety of input signal types. (See the *S650 Option datasheet* for full details).

This level of timing signal flexibility is unprecedented and can even eliminate the need for additional signal distribution chassis as there is no degradation in the precise quality of the coherent signals.



#### **Serial Time Outputs**

The dedicated Data/Timing port is provided to output NMEA-0183 or NENA PSAP strings. If NENA is selected, the serial Console port also supports the two-way timing aspects of the standard. In addition, the F8 and F9 Microsemi legacy time strings are also available.



### Oscillator Upgrades Improve Holdover Accuracy and Save Valuable Time

The standard S650 is equipped with a crystal oscillator that keeps the S650 accurate to nanoseconds when tracking GNSS. However, if GNSS connectivity is lost, thereby placing the server in holdover, the oscillator will begin to drift impacting timing accuracy. Upgrading the oscillator improves the holdover accuracy significantly. For example, consider the drift rates below for the standard oscillator compared to the OCXO and Rubidium upgrades:

#### Oscillator Holdover Drift

(1st 24 hours)

•	Standard	400 microseconds
•	OCXO	25 microseconds
•	Rubidium	<1 microsecond

The value of the upgraded oscillator is that if the GNSS signal is lost the S650 can continue to provide very accurate time and frequency. This provides personnel time to correct the problem with only gradual degradation or disruption in time synchronization accuracy.

## **Specifications**

#### **GNSS Receiver/Antenna**

- 72 parallel channel GNSS receiver
- GPS time traceable to UTC (USNO)
- Acquisition time: 30 seconds (cold start)
- Cable length: up to 900 ft. (275 m). See Options below.

#### **Time Accuracy**

< 15 ns RMS to UTC (USNO) at 1PPS output

After 1 day locked to GNSS; evaluated over normal environment (test range <+/-  $5^{\circ}$ F) defined in GR-2830

#### **Oscillator Aging (Monthly)**

#### **Holdover Accuracy**

1 day holdover, microseconds Standard Oscillator 400 μs OCXO Oscillator 25 μs Rubidium Oscillator <1 μs Evaluated over normal environment (test range <+/- 5°F) defined in GR-2830 after 3 days locked to GNSS

#### Frequency Ouput Accuracy and Stability

After 1 day locked to GNSS Frequency output accuracy:  $<1x10^{\mbox{-}12}$  @ 1day

#### **Network Protocols**

NTP SMTP Forwarding NTP Unicast, Autokey, SSHv2 MD5 IPv4/IPv6 SNTP Syslog 1 to 8 servers SNMP v2c. v3 Key management protocols Custom MIB can be individually disabled. DHCP/DHCPv6 PORT 1: Management & Time TACACS+ protocols LDAPv3 PORT 2, 3, and 4: Time RADIUS protocols only HTTPS/SSL

#### **NTP Server Performance**

- 10,000 NTP requests per second while maintaining accuracy associated with reference time source.
- Stratum 1 via GNSS: overall server timestamp accuracy of 5 microseconds to UTC with 1-sigma variation of 15 microseconds (typical). All NTP time stamps are hardware based or have realtime hardware compensation for internal asymmetric delays. The accuracy is inclusive of all NTP packet delays in and out of the server as measured at the network interface. The SyncServer easily supports many hundreds of thousands of NTP clients

• NTP Reflector option: 120,000 NTP client mode 3 requests per second. NTP packets time stamped 100% in hardware with prevailing clock accuracy. All non-NTP packets provided to the CPU on a bandwidth limited basis. The NTP Reflector included as part of the Security Protocol License Option\*.

#### Mechanical/Environmental

- Size: 1.73" x 17.24" x 15.88" (4.4 cm x 43.8 cm x 40.3 cm) 1U rack mount , including BNCs
- Power: 110/220 VAC, 50-60 Hz, 65 watts Optional 2nd power supply
- Operating temperature: Non Rb: -20°C to +65°C Rb: -5°C to +55°C
- Storage temperature: -40°C to +85°C (IEC 60068-2-1Ab (low temp soak), IEC 60068-2-2Bb (hi-temp soak), IEC 60068-2-14Nb (change of temp) IEC 60068-2-78Cb (humidity storage), IEC 60068-2-30Db (humidity condensation)
- Operational Humidity: <= 95%, non-condensing, IEC 60068-2-78Cb, IEC 60068-2-30Db
- Certifications: FCC Part 15, Class A, CISPR 22, Class A, UL/CSA 60950-1, IEC 60950-1, EN 60950-1, PSE, VCCI, RoHS 6/6
- Server weight: 12.5 lbs (5.7 kgs),
- Shipping package: 16.3 lbs (7.4 kgs)

#### Shock and Vibration:

Operational:	ETSI EN-300 019-2-3, Mil-STD-810G
Storage:	IEC 60068-2-6 Fc (sinusoidal vib)
	Mil-Std-810G, figure 514.6C-3
Transportation:	
Bounce	IEC 60068-2-27Ea (shock 18g)

Doditioo	120 00000 2 21 24 (010011 109)
Vibration	IEC 60068-2-64Fh (random vib)
Package drop	IEC 60068-2-31 Ec
Seismic:	EN300 019-2-3
	NEBS GR-63-CORE.

#### **Front Panel**

Display: Sharp, high-resolution 160x32 vacuum-fluorescent. Keypad: 0-9 numeric, up, down, left, right, ENTER, CLR, TIME, STATUS, MENU. Keypad lockout.

LEDs (tri-color green/red/orange)

- Sync: Time reference status
- Network: Network connection status
- Alarm: Fault condition

#### Rear Panel

Network:	Four RJ-45 100/1000Base-T Ethernet, Speed/ Duplex: Auto, 100/1000 full		
Serial Data/Timing:	NMEA-0183; ZDA/GGA/GSV/RMC messages; NENA 04-002 messages; DB9-F RS-232, user selectable rate to 115.2 kbps		
1PPS-Out:	BNC, Rising edge on-time, TTL into 50 $\Omega$		
GNSS:	BNC L1, 1575 MHz		
Console:	DB9-F RS-232		
Alarm Relay:	SPST ,maximum 300 mA and 32 V		
Power:	IEC 60320 C14 connector, optional second power supply/connector, hitless switching.		

#### Timing Input/Output Module (090-15201-0006)

	Input BNCs		Output BNCs					
Configuration	J1	J2	J3	J4	J5	J6	J7	J8
Standard	IRIG B AM 124 or 1PPS	10 MHz	IRIG B AM 124	10 MHz	IRIG B B004 DCLS	1PPS	off	off
FlexPort Option	IRIG B124 IRIG B004 IRIG B120 IRIG B000 IEEE-1344 1PPS 10MPPS	1 MHz 5 MHz 10 MHz	124 DCLS   FlexPort J3-J8 Software Selectable Outputs per BNC (Configured via the web interface):   a) Pulse:   i) Fixed Rate: 10/5/1MPPS, 100/10/1/kPPS, 100/10/1/0.5PPS   ii) Programmable Period: 100 ns to 2 sec, step size of 10 ns   b) Timecode: IRIG B 000/004/1344 DCLS, 120/124/1344 AM   c) Sine: 1/5/10 MHz					interface):

Signal Levels	
IRIG-In	AM: Ratio 2:1 to 3.5:1 Amp: 1 V to 8 V p-p, into 50 DCLS: <1.5 V for logic 0, >2 V for logic 1
IRIG-Out	AM: Ratio 10:3, Amp: $3.5 \pm 0.5$ Vpp, Zout 50 $\Omega$ DCLS: <0.8 V for logic 0, >2.4 V for logic 1, Zout 50 $\Omega$ for logic 0, >2.4 V for logic 1, Zout 50 $\Omega$
1PPS-In	Rising edge active, TTL into 50 $\Omega$
Rate/Pulse/1PPS- Out	Rising edge on-time, TTL into 50 $\Omega$
1,5,10 MHz-In	Sine wave, 1 Vpp to 8 Vpp, into 50 $\Omega$
1/5/10 MHz-Out	Sine wave 2.6 Vpp into 50 $\Omega$
10 MPPS In	$<$ 1 V for logic 0, $>$ 2 V for logic 1, into 50 $\Omega$

#### **Output Stability (10 MHz)**

(Measured on any 10MHz output) module

Oscillator	1S	10S	100S	1kS	10kS
Standard	<1e <sup>-9</sup>	<2e <sup>-10</sup>	<1e <sup>-10</sup>	<1e <sup>-11</sup>	<1e <sup>-12</sup>
OCXO	<1e-9	<5e-11	<5e-11	<7e-12	<7e-13
Rubidium	<2e <sup>-10</sup>	<3e-11	<3e-11	<5e <sup>-12</sup>	<5e <sup>-13</sup>

#### **Options**

- Timing Input/Output Module
- FlexPort Option to enable software selectable signals on Timing I/O module BNCs
- Security License Upgrade option for Security-Hardened NTP Reflector\*, RADIUS, LDAP, TACACS+, NTP Autokey
- Dual power supplies (with dual connectors)
- Rubidium or OCXO oscillator upgrade for extended holdover
- Antenna kits, cables, lightning arrestors, inline amplifiers, etc. are documented in the SyncServer S600/S650 Options Datasheet
- Domain Time II Comprehensive time client, server & management software for easy distribution, management and monitoring of time across Windows networks.



SyncServer S650 shown with two optional Timing I/O Modules

\* NTP Reflector is part of the Security Protocol License and will appear in version 1.1 due April 2016.

## **Product Includes**

SyncServer S650 (no option modules installed in base unit), locking power cord, and rack mount ears. Two-year hardware warranty. Current manual and MIB are available online at *www.microsemi.com*.

SyncServer S650 (base)+Timing I/O Module: 090-15200-651 SyncServer S650 (base) +Timing I/O Module+Rubidium: 090-15200-652

To add more options or Configure-to-Order, contact factory.

Microsemi makes no warranty, representation, or guarantee regarding the information contained herein or the suitability of its products and services for any particular purpose, nor does Microsemi assume any liability whatsoever arising out of the application or use of any product or circuit. The products sold hereunder and any other products sold by Microsemi have been subject to limited testing and should not be used in conjunction with mission-critical equipment or applications. Any performance specifications are believed to be reliable but are not verified, and Buyer must conduct and complete all performance and other testing of the products, alone and together with, or installed in, any end-products. Buyer shall not rely on any data and performance specifications or parameters provided by Microsemi. It is the Buyer's responsibility to independently determine suitability of any products and to test and verify the same. The information provided by Microsemi hereunder is provided "as is, where is" and with all faults, and the entire risk associated with such information is entirely with the Buyer. Microsemi does not grant, explicitly or any patent rights, licenses, or any other IP rights, whether with regard to such information itself or anything described by such information provided in this document is proprietary to Microsemi reserves the right to make any changes to the information in this document or to any products and services at any time without notice.



Microsemi Corporate Headquarters One Enterprise, Aliso Viejo, CA 92656 USA Within the USA: +1 (800) 713-4113 Outside the USA: +1 (949) 380-6100 Sales: +1 (949) 380-6136 Fax: +1 (949) 215-4996 email: sales.support@microsemi.com www.microsemi.com Microsemi Corporation (Nasdaq: MSCC) offers a comprehensive portfolio of semiconductor and system solutions for communications, defense & security, aerospace and industrial markets. Products include high-performance and radiation-hardened analog mixed-signal integrated circuits, FPGAs, SoCs and ASICs; power management products; timing and synchronization devices and precise time solutions, setting the world's standard for time; voice processing devices; RF solutions; discrete components; security technologies and scalable anti-tamper products; Ethernet Solutions; Power-over-Ethernet ICs and midspans; as well as custom design capabilities and services. Microsemi is headquartered in Aliso Viejo, Calif., and has approximately 3,600 employees globally. Learn more at www.microsemi.com.

©2016 Microsemi Corporation. All rights reserved. Microsemi and the Microsemi logo are registered trademarks of Microsemi Corporation. All other trademarks and service marks are the property of their respective owners.